

COMPLEMENTARY SILICON PLASTIC POWER TRANSISTORS

... designed for use in general purpose power amplifier and switching applications.

FEATURES:

- * Collector-Emitter Sustaining Voltage -

$V_{CE(sus)} = 40V(\text{Min})$ - TIP29, TIP30

60V(Min)- TIP29A, TIP30A

80V(Min)- TIP29B, TIP30B

100V(Min)-TIP29C, TIP30C

- * Collector-Emitter Saturation Voltage- $V_{CE(sat)} = 0.7V(\text{Max}) @ I_C = 1.0 A$

- * Current Gain-Bandwidth Product $f_T = 3.0 \text{ MHz}(\text{Min}) @ I_C = 200 \text{ mA}$


MAXIMUM RATINGS

Characteristic	Symbol	TIP29 TIP30	TIP29A TIP30A	TIP29B TIP30B	TIP29C TIP30C	Unit
Collector-Emitter Voltage	V_{CEO}	40	60	80	100	V
Collector-Base Voltage	V_{CBO}	40	60	80	100	V
Emitter-Base Voltage	V_{EBO}	5.0				V
Collector Current - Continuous - Peak	I_C	1.0 3.0				A
Base Current	I_B	0.4				A
Total Power Dissipation@ $T_C = 25^\circ\text{C}$ Derate above 25°C	P_D	30 0.24				W W/ $^\circ\text{C}$
Operating and Storage Junction Temperature Range	T_J, T_{STG}	-65 to +150				$^\circ\text{C}$

THERMAL CHARACTERISTICS


Characteristic	Symbol	Max	Unit
Thermal Resistance Junction to Case	$R_{\theta jc}$	4.167	$^\circ\text{C/W}$

FIGURE -1 POWER DERATING




NPN	PNP
TIP29	TIP30
TIP29A	TIP30A
TIP29B	TIP30B
TIP29C	TIP30C

1.0 AMPERE
COMPLEMENTARY SILICON
POWER TRANSISTORS
40-100 VOLTS
30 WATTS



TO-220



PIN 1.BASE
2.COLLECTOR
3.EMITTER
4.COLLECTOR(CASE)

DIM	MILLIMETERS	
	MIN	MAX
A	14.68	16.00
B	9.78	10.42
C	5.02	6.60
D	13.00	14.62
E	3.10	4.19
F	2.41	2.67
G	1.10	1.67
H	0.69	1.01
I	3.21	4.98
J	1.14	1.40
K	2.20	3.30
L	0.28	0.61
M	2.48	3.00
O	3.50	4.00

TIP29, TIP29A, TIP29B, TIP29C NPN / TIP30, TIP30A, TIP30B, TIP30C PNP

ELECTRICAL CHARACTERISTICS ($T_c = 25^\circ\text{C}$ unless otherwise noted)

Characteristic	Symbol	Min	Max	Unit
----------------	--------	-----	-----	------

OFF CHARACTERISTICS

Collector-Emitter Sustaining Voltage(1) ($I_C = 30\text{ mA}$, $I_B = 0$)	TIP29,TIP30 TIP29A,TIP30A TIP29B,TIP30B TIP29C,TIP30C	$V_{CEO(sus)}$	40 60 80 100	V
Collector Cutoff Current ($V_{CE} = 30\text{ V}$, $I_B = 0$) ($V_{CE} = 60\text{ V}$, $I_B = 0$)	TIP29,TIP30,TIP29A,TIP30A ←TIP29B,TIP30B,TIP29C,TIP30C	I_{CEO}	0.3 0.3	mA
Collector Cutoff Current ($V_{CE} = 40\text{ V}$, $V_{EB} = 0$) ($V_{CE} = 60\text{ V}$, $V_{EB} = 0$) ($V_{CE} = 80\text{ V}$, $V_{EB} = 0$) ($V_{CE} = 100\text{ V}$, $V_{EB} = 0$)	TIP29,TIP30 TIP29A,TIP30A TIP29B,TIP30B TIP29C,TIP30C	I_{CES}	0.2 0.2 0.2 0.2	mA
Emitter Cutoff Current ($V_{EB} = 5.0\text{ V}$, $I_C = 0$)		I_{EBO}	1.0	mA

ON CHARACTERISTICS (1)

DC Current Gain ($I_C = 0.2\text{ A}$, $V_{CE} = 4.0\text{ V}$) ($I_C = 1.0\text{ A}$, $V_{CE} = 4.0\text{ V}$)	h_{FE}	40 15	75	
Collector-Emitter Saturation Voltage ($I_C = 1.0\text{ A}$, $I_B = 125\text{ mA}$)	$V_{CE(sat)}$		0.7	V
Base-Emitter On Voltage ($I_C = 1.0\text{ A}$, $V_{CE} = 4.0\text{ V}$)	$V_{BE(on)}$		1.3	V

DYNAMIC CHARACTERISTICS

Current Gain - Bandwidth Product (2) ($I_C = 200\text{ mA}$, $V_{CE} = 10\text{ V}$, $f = 1\text{ MHz}$)	f_T	3.0		MHz
Small Signal Current Gain ($I_C = 200\text{ mA}$, $V_{CE} = 10\text{ V}$, $f = 1\text{ kHz}$)	h_{fe}	20		

(1) Pulse Test: Pulse width $\leq 300\text{ }\mu\text{s}$, Duty Cycle $\leq 2.0\%$

(2) $f_T = |h_{fe}| \cdot f_{TEST}$

FIG-2 TURN-ON TIME




FIG-4 DC CURRENT GAIN




FIG-6 ACTIVE REGION SAFE OPERATING AREA




FIGURE 3 - SWITCHING TIME EQUIVALENT CIRCUIT





FIG-5 TURN-OFF TIME



There are two limitation on the power handling ability of a transistor: average junction temperature and second breakdown safe operating area curves indicate I_C - V_{CE} limits of the transistor that must be observed for reliable operation i.e., the transistor must not be subjected to greater dissipation than curves indicate.

The data of FIG-6 curve is base on $T_{J(PK)} = 150^\circ\text{C}$; T_C is variable depending on power level. second breakdown pulse limits are valid for duty cycles to 10% provided $T_{J(PK)} \leq 150^\circ\text{C}$. At high case temperatures, thermal limitation will reduce the power that can be handled to values less than the limitations imposed by second breakdown.

Notice

MOSPEC reserves the rights to make changes of the content herein the document anytime without notification. MOSPEC or anyone on its behalf, assumes no responsibility or liability for any errors or inaccuracies. Please refer to MOSPEC website for the last document.

MOSPEC disclaims any and all liability arising out of the application or use of any product including damages incidentally and consequentially incurred.

Application shown on the herein document are examples of standard use and operation. Customers are responsible for comprehending suitable use in particular applications. MOSPEC makes no representation or warranty that such application will be suitable for the specified use without further testing or modification.

The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by MOSPEC for any infringements of patents or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of MOSPEC or others.

These MOSPEC products are intended for usage in general electronic equipment. Please make sure to consult with MOSPEC before you use these MOSPEC products in equipment which require specialized quality and/or reliability, and in equipment which could have major impact to the welfare of human life (atomic energy control, aeronautics , traffic control, combustion control, safety devices etc.)