

Switchmode Full Plastic Dual Schottky Barrier Power Rectifiers

Designed for use in switching power supplies. inverters and as free wheeling diodes. These state-of-the-art devices have the following features:

- *Glass Passivated chip junctions
- *Low Reverse Leakage Current
- *Fast Switching for High Efficiency
- *150°C Operating Junction Temperature
- *Low Stored Charge Majority Carrier Conduction
- *Low Forward Voltage , High Current Capability
- * Plastic Material used Carries Underwriters Laboratory

Flammability Classification 94V-O



* In compliance with EU RoHs 2002/95/EC directives

MAXIMUM RATINGS


Characteristic	Symbol	FRF1220K	Unit
Peak Repetitive Reverse Voltage Working Peak Reverse Voltage DC Blocking Voltage	V _{RRM} V _{RWM} V _R	200	V
RMS Reverse Voltage	V _{R(RMS)}	140	٧
Average Rectifier Forward Current (per diode) Total Device (Rated V _R),T _C =100°C	I _{F(AV)}	6 12	А
Peak Repetitive Forward Current (Rate V _R , Square Wave, 20kHz, T _C =125°C)	I _{FM}	12	А
Non-Repetitive Peak Surge Current (Surge applied at rate load conditions halfware, single phase, 60Hz)	I _{FSM}	80	А
Operating and Storage Junction Temperature Range	T_J,T_stg	-65 to +150	$^{\circ}$


ELECTRIAL CHARACTERISTICS

LECTRIAL GHARAGTERIOTIOS				
Characteristic	Symbol	FRF1220K	Unit	
Maximum Instantaneous Forward Voltage ($I_F = 6 \text{ Amp } T_C = 25^{\circ}C$)	V _F	1.1	V	
Maximum Instantaneous Reverse Current (Rated DC Voltage, T _C = 25°C) (Rated DC Voltage, T _C = 125°C)	I _R	1 100	uA	
Reverse Recovery Time ($I_F = 0.5 \text{ A}$, $I_R = 1.0$, $I_{rr} = 0.25 \text{ A}$)	Trr	35	ns	
Typical Junction Capacitance (Reverse Voltage of 4 volts & f=1 MHz)	C _P	55	₽F	


FAST RECOVERY RECTIFIERS

12 AMPERES 200 VOLTS






Г				
DIM	MILLIMETERS			
	MIN	MAX		
Α	14.90	15.15		
В	13.35	13.55		
С	10.00	10.10		
D	6.55	6.65		
Е	2.65	2.75		
F	1.55	1.65		
G	1.15	1.25		
Н	0.55	0.65		
- 1	2.50	2.60		
J	3.00	3.20		
K	1.10	1.20		
L	0.55	0.65		
М	4.40	4.60		
Ν	1.15	1.25		
0	3.35	3.45		
Р	2.65	2.75		
Q	3.15	3.25		
R	3.60	3.80		




FRF1220K

FIG-1 TYPICAL FORWARD CHARACTERISITICS



FORWARD VOLTAGE (Volts)

FIG-2 TYPICAL REVERSE CHARACTERISTICS



PERCENT OF PEAK REVERSE VOLTAGE (%)

50 Ω NI 10 Ω NI Under Test 50 Vdc Pulse Approx (Note 2) (--) 1Ω **ξ**ΝΙ Oscilloscope (Note 1)

- 1. Rise Time = 7 ns max. Input Impedance =1 M Ω , 22 pF 2. Rise Time = 10 ns max. Input Impedance = 50 Ω

FIG-3 FORWARD CURRENT DERATING CURVE




FIG-4 TYPICAL JUNCTION CAPACITANCE






FIG-5 PEAK FORWARD SURGE CURRENT





Set time base for 20/50 ns/cm

FIG-6 Reverse Recovery Time Characteristic and Test Circuit Diagram



Notice

MOSPEC reserves the rights to make changes of the content herein the document anytime without notification. MOSPEC or anyone on its behalf, assumes no responsibility or liability for any errors or inaccuracies. Please refer to MOSPEC website for the last document.

MOSPEC disclaims any and all liability arising out of the application or use of any product including damages incidentally and consequentially incurred.

Application shown on the herein document are examples of standard use and operation. Customers are responsible for comprehending suitable use in particular applications. MOSPEC makes no representation or warranty that such application will be suitable for the specified use without further testing or modification.

The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by MOSPEC for any infringements of patents or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of MOSPEC or others.

These MOSPEC products are intended for usage in general electronic equipment. Please make sure to consult with MOSPEC before you use these MOSPEC products in equipment which require specialized quality and/or reliability, and in equipment which could have major impact to the welfare of human life (atomic energy control, aeronautics, traffic control, combustion control, safety devices etc.)