

URAF0805 Thru URAF0820

Switchmode Full Plastic Dual Ultrafast Power Rectifiers

...Designed for use in switching power supplies. inverters and as free wheeling diodes. These state-of-the-art devices have the following features:

- * High Surge Capacity
- * Low Power Loss, High efficiency
- * Glass Passivated chip junctions
- * 150 Operating Junction Temperature
- * Low Stored Charge Majority Carrier Conduction
- * Low Forward Voltage, High Current Capability
- * High-Switching Speed 35 Nanosecond Recovery Time
- * Plastic Material used Carries Underwriters Laboratory

Plating pb free is indicated by box




MAXIMUM RATINGS

Characteristic	Symbol	URAF08				Unit	
Characteristic	Symbol	05	10	15	20	Unit	
Peak Repetitive Reverse Voltage Working Peak Reverse Voltage DC Blocking Voltage	V _{RRM} V _{RWM} V _R	50	100	150	200	V	
RMS Reverse Voltage	V _{R(RMS)}	35	70	105	140	V	
Average Rectifier Forward Current Per Leg T _C =125	I _{F(AV)}		8	.0		A	
Peak Repetitive Forward Current (Rate V_R , Square Wave, 20kHz,T _C =125)	I _{FM}		8	.0		A	
Non-Repetitive Peak Surge Current (Surge applied at rate load conditions half-ware, single phase, 60Hz)	I _{FSM}		1	50		A	
Operating and Storage Junction Temperature Range	T _J , T _{stg}		-65 to	+150			


ELECTRIAL CHARACTERISTICS

Characteristic	Symbol	URAF08				linit
Characteristic	Symbol	05	10	15	20	Unit
Maximum Instantaneous Forward Voltage ($I_F = 8.0 \text{ Amp } T_C = 25$) ($I_F = 8.0 \text{ Amp } T_C = 125$)	VF	0.975 0.870			V	
Maximum Instantaneous Reverse Current (Rated DC Voltage, $T_C = 25$) (Rated DC Voltage, $T_C = 125$)	I _R	10 200			uA	
Reverse Recovery Time ($I_F = 0.5 \text{ A}$, $I_R = 1.0$, $I_{rr} = 0.25 \text{ A}$)	Trr	35		ns		
Typical Junction Capacitance (Reverse Voltage of 4 volts & f=1 MHz)	CP		10	00		₽F





DIM A B C	MIN 15.05 13.35	MAX 15.15
В		15.15
	13.35	
С		13.45
	10.00	10.10
D	6.55	6.65
Е	2.65	2.75
F		1.00
G	1.15	1.25
Н	0.55	0.65
I	4.80	3.20
J	3.00	3.20
К	1.10	1.20
L	0.55	0.65
Μ	4.40	4.60
Ν	1.15	1.25
Р	2.65	2.75
0	3.35	3.45
Q	3.15	3.25



CASE Suffix "R"




ULTRA FAST

8 AMPERES 50-200 VOLTS


URAF0805 Thru URAF0820

FIG-1 TYPICAL FORWARD CHARACTERISITICS



FORWARD VOLTAGE (Volts)





PERCENT OF PEAK REVERSE VOLTAGE (%)

FIG-3 FORWARD CURRENT DERATING CURVE




FIG-4TYPICAL JUNCTION CAPACITANCE







FIG-5PEAK FORWARD SURGE CURRENT



NUMBER OF CYCLES AT 60 Hz





Notes: 1. Rise Time = 7 ns max. Input Impedance = $1 M \Omega$, 22 pF

2. Rise Time = 10 ns max. Input Impedance = 50Ω

Set time base for 10/20 ns/cm FIG-6 Reverse Recovery Time Characteristic and Test Circuit Diagram



Notice

MOSPEC reserves the rights to make changes of the content herein the document anytime without notification. MOSPEC or anyone on its behalf, assumes no responsibility or liability for any errors or inaccuracies. Please refer to MOSPEC website for the last document.

MOSPEC disclaims any and all liability arising out of the application or use of any product including damages incidentally and consequentially incurred.

Application shown on the herein document are examples of standard use and operation. Customers are responsible for comprehending suitable use in particular applications. MOSPEC makes no representation or warranty that such application will be suitable for the specified use without further testing or modification.

The information contained herein is presented only as a guide for the applications of our products. No responsibility is assumed by MOSPEC for any infringements of patents or other rights of the third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of MOSPEC or others.

These MOSPEC products are intended for usage in general electronic equipment. Please make sure to consult with MOSPEC before you use these MOSPEC products in equipment which require specialized quality and/or reliability, and in equipment which could have major impact to the welfare of human life (atomic energy control, aeronautics , traffic control, combustion control, safety devices etc.)